More Power: 30 A


SL30.300

Input: 3 AC 400...500VOutput: 24...28V / 720W

• 92.5% efficiency

Ideal for parallel operation

Simple fusing











## Input

Input voltage	3 AC 400500 V, ± 15 % 47-63 Hz, Suitable for IT power systems
<ul> <li>Rated Tolerances</li> <li>Continuous operation</li> <li>Short term (1 min) at 24 V/30 A</li> </ul>	340-576 V AC resp. 450-820 V DC 300-620 V AC resp. 420-890 V DC
Input current	3 x 2.0 A
Inrush current	< 17 A bei 576 V AC

Inrush current limiting done with a fixed 47R resistor (not a thermistor) which is bridged after the unit is running, so losses are minimised. That means no reset time even at a warm-start.

Fuse loading < 2 A<sup>2</sup>s

To be fused with a  $3 \times 10A$ , B-type 'circuit-breaker' switch based on the usual thermomagnetic overload sensing principle (used anyway to fuse the input lines; unit has no internal fuses).

Harmonic current emissions (PFC)	acc. EN 61000-3-2
Transient handling	Active transient filter incorporated, so transient resistance acc.to VDE 0160 / W2 (1560 V / 1.3 ms), for <i>all</i> load conditions.
Hold up time	> 10 ms at 400 V AC, 24 V / 30 A

# Efficiency, Reliability etc. \*

Efficiency	typ. 92.5 % (400 VAC, 24 V / 30 A)	
Losses	typ. 60 W (400 VAC, 24 V / 30 A)	
MTBF	425,000 h @ 400 VAC, 360,000 h @ 480 VAC (Siemensnorm SN 29500 (Release 07.97), 24 V/30 A, T <sub>amb</sub> = +40 °C)	С
Life cycle (electrolytics)	The unit exclusively uses longlife electrolyt specified for +105°C (cf. 'The SilverLine', p. High reliability and lifetime, as  only four aluminium electrolytics and no small aluminium electrolytics are use	2).

# **Output**

Output voltage	2428 V DC, adjustable by (covered) front panel potentiometer. Adj. range guaranteed
Output noise suppression	EN 61000-6-3 (class B) is fulfilled even when using long, unscreened output cabels
Ambient temperature range T <sub>amb</sub>	Operation: 0°C+70°C (>60°C: Derating) Storage: -25°C+85°C
Rated continuous loadii at T <sub>amb</sub> =0°C - 60°C	ng with convection cooling 24 V / 30 A (720 W) resp. 28 V / 26 A (728 W)
Derating	typ. 18 W/K (at T <sub>amb</sub> =+60°C+70°C)
Voltage regulation	better than 2% over all
Ripple  Output charact. S  Output charact. P (S/P Single/Parallel Mode)	(incl. spikes (20 MHz bandw.), $50 \Omega$ measurem.) < $20 \text{ mV}_{PP}$ (< $0.1 \%$ ) < $40 \text{ mV}_{PP}$ (In: 230VAC, Out: 24V/30A) < $100 \text{ mV}_{PP}$ (In: 184VAC, Out: 24V/30A)
Over-voltage protection	At 32 V ± 10%: switch to hiccup mode

Front panel indicators: • Green LED on, when  $V_{out} > U_T$ , where  $U_T$  is ca. 2 V below Vout adjusted (24V...28V)
• Red LED on, when 10 V <  $V_{out}$ <  $U_T$ • Red LED flashes, when 0 V <  $V_{out}$ < 10 V

Parallel operation Yes, up to ten SL30 units

To achieve current sharing the output V/I characteristic can be altered to be 'softer' (25V at 0.4A, 24V at 30A). This is done by repositioning a bridge connection (without opening the unit).

Power Back Immunity 35 V

#### **Construction / Mechanics \***

Housing dimensions and Weight

W x H x D
 Free space for ventilation
 Weight
 Weight
 W x H x D
 240 mm x 124 mm x 112 mm (+ DIN rail)
 above/below 70 mm recommended
 left/right 25 mm recommended
 Weight
 2.0 kg

Design advantages:

- All connection blocks are easy to reach as mounted at the front panel.
- PVC insulated cable can be used for all connections, as the connection blocks are mounted in the cooler area on the underside of the unit.
- \* For further information see data sheets "The SilverLine", "SilverLine Family Branches" and mechanics data sheet

### **Order information**

Order number	Description
SL30.300	
SLZ01	Screw mounting set, two needed per unit

sl30e300 / 050318 1/2



### **Start / Overload Behaviour**

Startup delay typ. 0.2 s

Rise time ca. 20-80 ms, depending on load

Duration of switch-on attempts at
Initial application ca. 1.4 s

on mains

• Subsequent ca. 0.5 s

attempts

Hiccup operation at  $V_{out}$  < ca. 10 V

Duration between ca. 1 s

switch-on attempts

Electronic current limiting, protects against overload and short circuit:

- V<sub>out</sub> < ca. 10 V: Periodical switch-on attempts (hiccup-mode).
- V<sub>out</sub> > ca. 10 V: The output current is continuous.

The V/I characteristic of the supply is straight.

Advantages of the switch-on/overload behaviour:

- Safer switch-on into highly non-linear loads with large starting currents
- Short-term overloads result in current limiting and not in an immediate shut-down.
- Parallel operation of several units possible.
   Proper switch-on performance is obtained.

#### **Further Information**

For further information, especially about


- EMC
- Connections
- Safety, Approvals
- · Mechanics und Mounting,

see page 2 of the "The SilverLine" data sheet.


#### For detailed dimensions

see SilverLine mechanics data sheet SL30


#### Output V/I characteristic (typ.)



### Efficiency (typ.)



# **Hold-up time** (min., at $V_{out}$ =24V)



Specifications valid for 3 x AC 400V input voltage, +25°C ambient temperature, and 5 min run-in time, unless otherwise stated. They are subject to change without prior notice.

# Your partner in power supply:





PULS GmbH

Arabellastraße 15
D-81925 München
Tel.: +49 89 9278-0
Fax: +49 89 9278-199
www.puls-power.com